


Fittings Mod. 6610


Single Banjo



| DIMENSIONS | | | | | | | | | |
|-------------|----|------|------|------|------|------|------|------------|------------------------------|
| Mod. | A | C | F | M | O | V | W | Weight (g) | assembled with Mod. |
| 6610 4-M5 | 4 | 5 | 9 | 19 | 9 | 5.1 | 9 | 9 | 1631 |
| 6610 4-M6 | 4 | 5 | 9 | 19 | 9 | 5.1 | 9 | 8 | SCU, SVU, SCO... |
| 6610 4-1/8 | 4 | 7.5 | 9 | 21.5 | 14.5 | 9.8 | ∅ 14 | 14 | 1631, 1635, SCU, SVU, SCO... |
| 6610 5-M5 | 5 | 5 | 10 | 20 | 9 | 5.1 | 9 | 9 | 1631 |
| 6610 5-M6 | 5 | 5 | 10 | 20 | 9 | 5.1 | 9 | 8 | SCU, SVU, SCO... |
| 6610 5-1/8 | 5 | 8 | 10 | 23 | 14.5 | 9.8 | ∅ 14 | 16 | 1631, 1635, SCU, SVU, SCO... |
| 6610 6-M5 | 6 | 6.5 | 12.7 | 22.5 | 9 | 5.1 | ∅ 10 | 12 | 1631 |
| 6610 6-M6 | 6 | 6.5 | 12.7 | 22.5 | 9 | 5.1 | ∅ 10 | 12 | SCU, SVU, SCO... |
| 6610 6-1/8 | 6 | 8 | 12.7 | 24 | 14.5 | 9.8 | ∅ 14 | 16 | 1631, 1635, SCU, SVU, SCO... |
| 6610 6-1/4 | 6 | 10 | 12.7 | 26 | 14.5 | 13.2 | ∅ 18 | 19 | 1631, 1635, SCU, SVU, SCO... |
| 6610 8-1/8 | 8 | 8 | 14.2 | 25.5 | 14.5 | 9.8 | ∅ 14 | 19 | 1631, 1635, SCU, SVU, SCO... |
| 6610 8-1/4 | 8 | 10 | 14.2 | 27.5 | 14.5 | 13.2 | ∅ 18 | 22 | 1631, 1635, SCU, SVU, SCO... |
| 6610 8-3/8 | 8 | 11 | 14.2 | 28.5 | 14.5 | 16.7 | ∅ 21 | 23 | 1631, 1635, SCU, SVU, SCO... |
| 6610 10-1/4 | 10 | 8.8 | 16.5 | 29 | 14.5 | 13.2 | ∅ 18 | 22 | 1635, SCU, SVU, SCO... |
| 6610 10-3/8 | 10 | 10.3 | 16.5 | 30.5 | 14.5 | 16.7 | ∅ 21 | 23 | 1635, SCU, SVU, SCO... |
| 6610 12-1/2 | 12 | 12,8 | 16,5 | 32 | 14,5 | 21 | ∅ 26 | 37 | 1635 |

Fittings Mod. 6811

Metric Male Adaptor Sprint®



| DIMENSIONS | | | | | | | |
|-------------|----|------|-----|------|------|----|------------|
| Mod. | G | D | H | T | L | SW | Weight (g) |
| 6811 4-M5 | 4 | M5 | 4 | 16.5 | 24.5 | 8 | 3 * |
| 6811 4-1/8 | 4 | G1/8 | 5.5 | 16.5 | 27.8 | 12 | 10 |
| 6811 5-1/8 | 5 | G1/8 | 5.5 | 18 | 29.3 | 12 | 9 |
| 6811 5-1/4 | 5 | G1/4 | 7 | 18 | 31 | 14 | 11 |
| 6811 6-1/8 | 6 | G1/8 | 5.5 | 18 | 29.3 | 12 | 10 |
| 6811 6-1/4 | 6 | G1/4 | 7 | 18 | 31 | 14 | 12 |
| 6811 8-1/8 | 8 | G1/8 | 5.5 | 20.5 | 31.8 | 12 | 12 |
| 6811 8-1/4 | 8 | G1/4 | 7 | 20.5 | 33.5 | 14 | 13 |
| 6811 10-1/4 | 10 | G1/4 | 7 | 23 | 36 | 14 | 16 |
| 6811 10-3/8 | 10 | G3/8 | 8 | 23 | 37.3 | 19 | 25 |
| 6811 12-3/8 | 12 | G3/8 | 8 | 24 | 38.3 | 19 | 25 |
| 6811 14-1/2 | 14 | G1/2 | 9 | 28 | 44 | 22 | 39 |

* = with O-Ring